


# Magnetic switch, Change-over, bistable with plug connector


Type 31160-NK

#### **External electrical connections**



- "Installed opposite to indication rail
- "Cable exit downwards

### **Dimensions**



#### **Instruction manual**

# Function Magnetic switch for WEKA- VLI

The magnetic switch is mounted outside of the float chamber opposite to the indication rail. The switching logic can be reversed by inverting the switch module with cable-exit upwards or by installing the switch module adjacent to the indication rail where technically authorised (see datasheet 20010501). The magnet inside the float activates the reed switch, when the liquid in the float chamber reaches that level.

Please refer to the safety guidelines.

Product code 31160-NK

(with counter plug, without cable)

Switching logic Change-over, bistable

Contact rating max. 230V max. 1A

max. 60VA max. 60W

Enclosure IP67 - plugged and locked (EN 60529)

Material

Housing Stainless steel 316 / 316L
Plug connector Brass: chromium-plated
Seal Perbunan (NBR)
Insert 3-pole + PE
Connection Solder-terminal
Cable cores max. 1mm
Cable diameter 66 8mm

Type label Polyester: silver, black printing

**Operating conditions** 

Media temperature	Ambient temperature
-50°Cõ +150°C	-20°Cõ +80°C

Media temperature Temperature of liquid within the float chamber

Ambient temperature Temperature of air around the magnetic switch

## **Fixation**

When ordering level indicators with switches, hose clamps are included.

When ordering switches as spare parts, hose clamps are never included and must be ordered seperately.

In case of ordering hose clamps pipe size must be indicated:

For pipe diameter 300 40mm Article no. 80648 For pipe diameter 400 57mm and 570 80mm Article no. 84043

Note

The switch is maintenance free.